

Features

- One or two ¼" call cord jacks (push-button and geriatric call cords are available)
- Illuminated reset button
- Dummy plugs available
- Call-assurance LEDs for each call cord jack
- UL/cUL® 1069 and UL® 2560 Listed
- RoHS Compliant

Description

The SF121 Single and SF122 Dual Patient Stations include one or two ¼" jacks for call cords, one or two call-assurance LEDs, and a single button to reset calls. Pressing the call cord's button registers a call at the NC415G3/NC404TS Master Station and LI122UN Room Controller with Dome Light.

Similarly, a call is registered if the call cord is accidentally removed from the call cord jack. Using an optional dummy plug prevents the station from placing a cord-out call.

Mount the station using an IH121K Single Station Mounting Kit, or mount two stations together using an IH122K Dual Station Mounting Kit. The station snaps into the kit's plastic bezel and then onto the kit's surface mounting plate, leaving no visible screw holes.

Required Components

IH121K Single Station or IH122K Dual Station Mounting Kit
LI122UN Room Controller with Dome Light, or PM120 Room Controller, or IR42xP5-series Stations
SF301A-series or SF301G-series call cords

Optional Components

JK018K Five (5) Dummy Plugs
RP131K Single-Gang Blank Plate (5 each)
NC415G3 or NC404TS Master Station



SF121 Single & SF122 Dual Patient Stations

Specifications

| | |
|---------------|--|
| Dimensions: | 4.58"H × 3.25"W × 1.03"D (116 mm × 83 mm × 26 mm) |
| Environment: | 5%–95% non-condensing humidity; 0°C–60°C |
| Construction: | PC board with quality electronic components mounted on a flame-retardant (UL® 94V-0) plastic faceplate |
| Mounting: | Attach included back plate to a standard single-gang ring or dual-gang ring and box |
| Connections: | 2-wire flying lead |

Listings



UL® 1069 Listed and cUL® Listed to CSA C22.2 No. 205; UL® File Number E71599.



RoHS Compliant.