

Features

- UL® 1069 Listed (when used with IR319B, IR320B, IR311E or IR312E patient stations).
- Provides on/off control of two lamp sources.
- Mounts directly to patient stations or pillow speaker intercom module (if used).

Description


The PM321B and PM322B Multiplex Lamp Control Modules are for use with the Tek-CARE®300III Nurse Call System using IR319B, IR320B, IR311E or IR312E patient stations and SF41ZKL or SF31ZDL pillow speakers. The modules provide on/off control through the pillow speaker of two lamp sources, typically the overhead room lamp and a separate reading lamp. Circuitry for low voltage lamp switching is provided by others. Turning the lamps on or off is accomplished by pressing the appropriate push buttons on the pillow speaker.

The lamp control module can be mounted directly to the patient station, or can be mounted to the station's PM311C or PM312C pillow speaker intercom module. Standard SF401-series or SF311-series call cords may be used without removing modules.

Listings



UL® 1069 listed; UL® File Number E71599.



PM322B Multiplex Lamp Control Module

Specifications

Dimensions:	5"W × 1.625"D × 0.5"H (127 mm × 41 mm × 13 mm)
Construction:	PC board with quality electronic components
Mounting:	Plug-in connectors mounted to patient station or to PM311C/PM312C (if used)
Wiring:	Multiplex

Required Components

Tek-CARE®300III Patient Stations

IR319B or IR320B Patient Stations
with SF41ZKL Pillow Speaker
-or-
IR311E or IR312E Patient Stations
with SF31ZDL Pillow Speaker